

METHOD AND APPARATUS FOR REDUNDANT LOCATION  
ADDRESSING USING DATA COMPRESSION

*Inv. a1*  
a1 →  
TECHNICAL FIELD

This invention generally concerns memory arrays, and more  
5 particularly, techniques for identifying and substituting for defective locations in  
memory arrays.

BACKGROUND OF THE INVENTION

Memory arrays consist of a number of storage locations or memory  
cells. Memory arrays are generally coupled to a storage control unit for  
10 accessing storage locations (cells) in order to store information in, or to retrieve  
information from, the memory array. Memory arrays are generally constructed  
in a reliable and robust manner. However, some random number of memory  
locations may be or become defective. It is desirable to avoid storing data to, or  
retrieving data from, defective memory locations. In order to avoid accessing  
15 defective memory locations, a memory map is generally devised to map  
addresses for defective memory array cells to another memory array or another  
portion of the memory array that is known to be operative. This memory array or  
portion is commonly referred to as a spare or a redundant memory array. The  
memory map is stored in another memory array, known as the map memory  
20 array. The size required for the spare and map memory arrays depends on the  
number of defective memory cells to be replaced. If the primary or first memory  
array requires that all locations be spared, the spare memory array will need to be  
as large as the first memory array and the map memory array will also need to be  
large. Since relatively few locations in the first memory array usually are  
25 defective, the size of the spare memory array is usually far less than the size of  
the primary or first memory array. It is desirable, of course, to make the spare  
and map memory arrays as small as possible, as unused locations dedicated to  
spare or map memory are wasted and this wastes resources. In order to

maximize the efficient use of memory resources, there is need for a method and corresponding apparatus for reducing the amount of data to be stored in the map memory array.

## SUMMARY OF THE INVENTION

5 Briefly stated, in a first embodiment, the present invention contemplates a method for identifying defective cells in a memory array. The method includes steps of receiving a request for accessing an address and analyzing the address to determine when the address matches an address stored in a temporary memory array. When the address does not match any address stored  
10 in the temporary memory array, the method includes steps of sending a wait instruction, analyzing the address to determine which portion of compressed data stored in a map memory array to decompress and decompressing the portion of compressed data to provide expanded data. The method also includes steps of writing the expanded data to the temporary memory array and comparing the  
15 expanded data to the address to determine when the address corresponds to an expanded datum of the expanded data.

In a second embodiment, the present invention includes a method for accessing a memory array. The method includes steps of requesting an address for one or more memory array cells comprising a first memory array and comparing the address to decompressed data describing defective memory array cells in the first memory array to determine when the address and a datum from the decompressed data match. The method includes a step of routing the address to a second memory array when the address and a datum from the decompressed data match.

25 In a third embodiment, the present invention includes a method for accessing a memory array. The method includes steps of receiving a memory array access request including a requested address, generating a first hash code from the requested address and comparing the first hash code to hash codes for decompressed addresses stored in a temporary memory array. When a match is

found between a hash code for a decompressed address and the first hash code, the method includes a step of routing the memory array address request to a spare memory array.

Another embodiment of the present invention includes a memory control circuit. The memory control circuit includes a storage control unit coupled to a bus. The storage control unit accesses memory array units to retrieve data from a first memory array unit in response to memory array access requests delivered via the bus. The memory control circuit also includes a first memory array coupled to the storage control unit. The first memory array is for temporarily storing data. The memory control circuit additionally includes a second memory array coupled to the storage control unit. The second memory array provides cells for replacing cells determined to be defective in the first memory array. The memory control circuit further includes a data compression circuit that compresses data describing memory array addresses corresponding to cells determined to be defective in the first memory array to provide compressed addresses. The data compression circuit also decompresses compressed addresses to provide decompressed addresses. The data compression circuit couples to the storage control unit.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is a block diagram of a computer system employing a compression engine in accordance with an embodiment of the present invention.

Figure 2 is a block diagram of the memory storage control unit in a preferred embodiment of the invention.

Figure 3 is a flowchart of a process for testing a memory array in accordance with another embodiment of the invention.

Figure 4 is a flowchart of a process for accessing primary and spare memory array cells in accordance with yet another embodiment the invention.

Figure 5 is a flowchart of a portion of the process of Figure 4, where the portion determines when a given memory cell location is defective.

## DETAILED DESCRIPTION OF THE INVENTION

Figure 1 is a block diagram of a computer system 10 that uses one embodiment of the present invention. The computer system 10 includes a central processing unit or CPU 12 coupled by a bus 17 to an input/output or I/O device 15 and to a storage control unit 20. In a preferred embodiment, the CPU 12 may be a 68040 processor available from Motorola of Phoenix, Arizona or a Pentium ® processor available from Intel of Santa Clara, California. I/O device 15 may comprise a keyboard, one or more disk data storage units, a display, a printer or coupling to external data sources such as a local area network or the like.

The storage control unit 20 couples via the bus 17 to a collection of memory devices including ROM 31, RAM 35 (*i.e.*, the primary memory or first memory array), a spare memory array 39, a map memory array 41 and a temporary memory array 43. The spare memory array 39, map memory array 41 and/or temporary memory array 43 may be included within the storage control unit 20, may comprise sections of RAM 35 reserved for this purpose or may comprise separate memory units.

The storage control unit 20 is coupled via bus 17 to the map memory array 41 and the temporary memory array 43. In operation, the CPU 12 operates on data from the I/O device 15 in response to commands retrieved from memory, either from ROM 31 or RAM 35 via the storage control unit 20, and also stores data via the storage control unit 20 into RAM 35. Memory cells in each of the memories ROM 31, RAM 35, spare memory array 39, map memory array 41 and temporary memory array 43 include a regular arrangement having a fixed number of dimensions. These dimensions are ordered in some fashion, *e.g.*, page, row and column. Each of these dimensions are then subdivided and numbered, for example, page 1, 2, 3 and the like. This common scheme specifies a regular structure, repeating for some interval. This also allows for easy accessing of data stored in the memory array as the page number, row number and column number are all that is necessary to access memory cells for

For example, if page 3, row 16, column 32 is the location of a defective storage cell, the map may need only the numbers 3, 16, 32 in order to provide a replacement memory cell. Replacement locations are normally assigned on a first come, first served basis. Thus, for every entry in the map memory array 41, a sequential replacement location may be assigned in the spare memory array 39. While this method allows efficient and easy access to replacement memory cells in the spare memory array 39, certain types of defects consume large amounts of the map memory array 41 storage space.

In the operation of the computer system 10 of Figure 1, the storage control unit 20 scrutinizes all memory access requests. When a particular memory access request matches an address encoded in the compressed data stored in the map memory array 41, *e.g.*, as discussed with respect to Figures 3 through 5, an address in the spare memory array 39 is substituted for the

requested address. This substituted address selects a memory cell from the spare memory array 39 instead of, for example, from RAM 35. This process requires some portion of the data in the map memory array 41 to be decoded from the compressed state (as stored in the map memory array 41), in order to utilize  
5 defective cell address data from the map memory array 41.

One way of accomplishing this is to use a hash coding algorithm. During data compression within storage control unit 20, a code word may be generated that points to each defective cell address from the RAM 35 mapped in the map memory array 41. A cyclic code or some other robust process may be  
10 used to quickly produce a unique code word for each defective cell address in the primary memory. This code word represents a "hash code" and may be used as an index into the decompressed addresses and their associated hash codes stored in temporary memory array 43.

One way to generate hash codes is to treat the address data as a  
15 contiguous series of bits, *i.e.*, as a number. This number is then divided by a prime number, such as 11. The most significant bits of the hash code provide an estimate of the address data and is useful as a quick index to a given number of replacement records in the map memory array 41.

When a hash code matching one of the hash codes stored in the  
20 temporary memory array 43 is produced by analysis of the address for the accessed memory cell site, the matching record in the temporary memory array 43 is used to redirect access to the spare memory array 39. When the comparison of the hash code for the address to which access is sought to the hash codes stored in the temporary memory array 43 produces a "miss" *i.e.*, the defective  
25 cell addresses in the primary memory array 35 are not available in expanded form in the temporary memory array 43, a wait request may be issued to the CPU 12 while the data stored in the map memory array 41 are decompressed by the storage control unit 20.

Alternatively, an estimate may be made as to the range of memory  
30 array addresses required and some of the compressed data from the map memory

004207 55250900

array 41 may be uncompressed by the storage control unit 20 and then stored in the temporary memory array 43. A least-recently-used algorithm may be used to specify replacement cell addresses from the temporary memory array 43.

In a preferred embodiment, the storage control unit 20 of Figure 1 is realized as illustrated by the block diagram of Figure 2. A first component 201 acts as a compression engine, to provide compressed data to, and to decompress compressed data from, the map memory array 41. The first component 201 also acts to set a compression flag for the hash code in the hash code storage area of the map memory array 41. A hash code generator 203 generates hash codes from addresses using any known method for providing truncated codes as indices. A hash code correlator 205 takes error location and hash code data and uses the hash code to quickly approximate addresses corresponding to bad cell address data stored in the map memory array 41. A relocation record register 207 stores one relocation record to provide access to relocated data, *i.e.*, data corresponding to the address currently being accessed in spare memory array 39.

A hash code register stack 209 stores hash codes for uncompressed address data from the map memory array 41 that are stored in the temporary memory array 43. The hash code register stack 209 provides quick reference to the storage addresses corresponding to defective memory locations in RAM 35 that have been most recently accessed and includes records for hash codes corresponding to memory locations that are currently stored in an uncompressed state, for example, in temporary memory array 43. An error detection code generator 211 provides and stores a check code every time a memory location is accessed for a write operation. When the same memory location is read, another check code is generated and is compared with the earlier check code generated during the write operation. When the two code words differ, an error has occurred. The error check operation may be implemented using any known method, including methods as simple as parity checking or as thorough as the Reed-Solomon technique.

While Figure 2 shows the computer system 10 as implementing the storage control unit 20 as a stand-alone unit, it will be appreciated that storage control unit 20 or one or more of the associated functions may be implemented in a number of other ways. For example, one or more of the functions of the storage control unit 20 may be included in software or in instructions contained in the ROM 31 and executed by the processor 12. Alternatively, one or more of the functions of the storage control unit 20, the spare memory array 39, the map memory 41 and the temporary memory array 43 may be implemented in the integrated circuit(s) comprising RAM 35.

Figure 3 is a flow chart of a process 50 for testing a memory array to generate addresses of defective memory array cells in, for example, RAM 35, for compressing data describing defective memory array cell locations and for storing the compressed data describing defective memory array cell locations in the map memory array 41. Generally, the process 50 may be invoked on any sort



5

10

15

25

30

86. When not all memory array access requests have been processed, control passes to request access to one or more memory array cells in step 74.

When the query task 76 determines that a requested address is for a defective memory array cell, a spare memory array address is obtained from the temporary memory array 43 in step 80, and a cell in the spare memory array 39 is accessed in step 82. Control then passes to the query task 84 to determine whether or not all memory array access requests have been executed.

Figure 5 is a flow chart showing the query task 76 in more detail. The query task 76 begins with a query task 90 to determine if the address is in a range of addresses stored in the temporary memory array 43. When the requested address is in the range of addresses stored in the temporary memory array 43, control passes to a query task 100 to determine if the requested address corresponds to a defective memory array cell. The "yes" and "no" options of the query task 100 correspond to the "yes" and "no" options shown with query task 76 of Figure 4.

When the address that is requested is not in the range of the temporary addresses stored in the temporary memory array 43, an optional "wait" signal may be passed in step 92 to the unit requesting memory access, such as the CPU 12 of Figure 1. In one embodiment, a range of data to be decompressed from the map memory array 41 are estimated in step 94, and data falling within this range are decompressed in step 96 via the storage control unit 20 of Figure 1. The decompressed address data are stored in step 97 in the temporary memory array 43 of Figure 1. An optional "end wait" signal may then be sent in step 98 to the unit requesting memory access, for example, the CPU 12. Control then passes back to the query task 100 to determine if the requested address corresponds to one of the decompressed addresses for defective memory cells stored in the temporary memory array 43.

The invention as described may allow a memory array to be operated more efficiently by reducing the number of memory cells needed in order to store a map of defective memory cells in the memory array. It may be

From the foregoing it will be appreciated that, although specific  
5 embodiments of the invention have been described herein for purposes of  
illustration, various modifications may be made without deviating from the spirit  
and scope of the invention. Accordingly, the invention is not limited except as  
by the appended claims.